

<b>Pressure Vs Torque Conversion Chart</b>			
<i>Titan LP2 Low Profile</i>			
<b>Pressure</b>	<i>Torque</i>		<b>Pressure</b>
<b>Psi</b>	<i>Ft-Lb</i>		<b>Mpa</b>
			<i>Nm</i>
1500	268		10
1600	286		11
1800	322		12
2000	360		14
2200	396		15
2400	431		17
2600	467		18
2800	503		19
3000	541		21
3200	577		22
3400	614		23
3600	650		25
3800	686		26
4000	724		28
4200	760		29
4400	796		30
4600	833		32
4800	869		33
5000	904		34
5200	940		36
5400	976		37
5600	1013		39
5800	1049		40
6000	1087		41
6200	1123		43
6400	1159		44
6600	1196		46
6800	1232		47
7000	1271		48
7200	1307		50
7400	1343		51
7600	1380		52
7800	1416		54
8000	1459		55
8200	1496		57
8400	1532		58
8600	1568		59
8800	1605		61
9000	1640		62
9200	1676		63
9400	1713		65
9600	1749		66
9800	1785		68
10000	1826		69